

GORAN GENERATOR



GGC220 GENSET

Generating Set Powered By



STAMFORD

Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	160KWe / 200KVA	176KWe / 220KVA
1800rpm, 60 Hz / 440V	180KWe / 225KVA	200KWe / 250KVA

Genset Specifications

Engine Make & Model	Cummins 6CTAA8.3G7
Origin	China
Alternator Type	Stamford UCI274H
Control Panel	Deap Sea - 6110
Circuit Breaker Type	3 Pole MCCB
Water Cooling System	
Electronic Governor	
Electrical Stop Solenoid, Energized to Run	
Compact Size	

Fuel System

	%50	%75	%100
1500rpm, 50 Hz	23	34	45
1800rpm, 60Hz	27	39	53

*Prime Power (l/hr)

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG32-I, IEC34 CSA C-22.2100, AS 1359, BS 1 6861, B En -6-610002:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. $1 \text{ hp} = 1 \text{ kW} \times 1.36$

Engine Technical Data


No. of Cylinders / Alignment	6/ In Line
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	114
Stroke, mm	135
Displacement, l	8.3
Compression Ratio	16.7:1
Starting	24V Electric
Alternators, Amps	24V/40A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	SX460
Protection	IP23
Temperature Rise, °C	125
Regulation	%1.0±
No. of Phases	3
No. of Poles	4

Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
2.90	1.08	1.90	1925	315



GGC220 GENSET

Generating Set Powered By



STAMFORD

Performances

	1500rpm	1800rpm
Alternator Efficiency	%93.3	%93.2
Engine Power		
Prime Power, KWm(hp)	230(172)	268(200)
Standby Power, KWm(hp)	257(192)	296(221)
Alternator		
Prime Power, KWe	160	196

Lubrication System

	1500rpm	1800rpm
Oil Consumption (l/hr)	0.10	0.10
Oil Sump Capacity, l	18.9	
Oil System Capacity Include Filters, l	23.8	

Cooling System

	1500rpm	1800rpm
Heat Radiation from Engine and Alternator, Power KW	27	22
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	72	81
Radiator Cooling Air Flow, m³/s (cfm)	9040(256)	11336(321)
Coolant Capacity, l	65.6	

Intake & Exhaust System

	1500rpm	1800rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	631(17.88)	890(25.2)
Heat Rejection Exhaust at Standby Power, KW	160	190
Exhaust Gas Temperature at Standby °C	493	467
Max Allowable Back Pressure in Exhaust Line, Kpa	10	10
Exhaust Gas Flow at Standby Power, m³/min(cfm)	-	-

Accessories

Oil Drain Pump	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Oil
Oil (VDS40/15 3)	Genuine Coolant
Coolant 'Ready Mix'	Fuel Tank Base Frame for 8hrs
Standard Silencer	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
 - Battery Disconnect Switch
 - Electrical Governor
- **Alternator**
 - Excitation Boost System (EBS)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)

Genuine - Cummins

Oil filter	(1)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

GORAN

GENERATOR

✉ gorangenerator@gorangroup.com

🏠 Iraq-Erbil-60M str.

☎ 07504483162 - 07704483162

🌐 www.gorangroup.com