

# GORAN GENERATOR

## GGP330 GENSET

Generating Set Powered By  Perkins **STAMFORD**



Image for illustration purposes only

### Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	240KWe / 300KVA	264KWe / 330KVA
1800rpm, 60 Hz / 440V	282KWe / 352KVA	309KWe / 386KVA

### Genset Specifications

Engine Make & Model	Perkins I506A-E88TAG5
Origin	USA
Alternator Type	Stamford HCI444D
Control Panel	Deap Sea - 7310
Circuit Breaker Type	3 Pole MCCB
Tropical Cooling System	
Digital Electronic Governor	
Turbocharged	
Exceptional Power to Weight Ratio	

### Fuel System

	%50	%75	%100
1500rpm, 50 Hz	33	48.2	64.9
1800rpm, 60Hz	38.9	56.8	77.1

\*Prime Power (l/hr)

### International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.  
Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG32-I, IEC34 CSA C-22.2100, AS 1359, BS 1 6861, B En -6-610002:2001



### RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

### Engine Technical Data


No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	112
Stroke, mm	149
Displacement, l	8.8
Compression Ratio	16.1:1
Starting	24V Electric
Alternators, Amps	24V/45A

### Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440
Protection	IP23
Temperature Rise, °C	125
Regulation	%1.0±
No. of Phases	3
No. of Poles	4

### Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
3.0	1.0	1.85	2150	310



# GGP330 GENSET

Generating Set Powered By  Perkins **STAMFORD**

Performances	1500rpm	1800rpm
<b>Alternator Efficiency</b>	%93	%93
<b>Engine Power</b>		
Prime Power, KWm(hp)	358(267)	402(300)
Standby Power, KWm(hp)	393(293)	446(333)
<b>Alternator</b>		
Prime Power, KWe	240	288

Lubrication System	1500rpm	1800rpm
<b>Oil Consumption (l/hr)</b>	%0.1 of fuel consumption	
<b>Oil Sump Capacity, l</b>	36	
<b>Oil System Capacity Include Filters, l</b>	41	

Cooling System	1500rpm	1800rpm
<b>Heat Radiation from Engine and Alternator, Power KW</b>	8	8
<b>Heat Rejection to Coolant and Lube Oil at Standby Power, KW</b>	125	138
<b>Radiator Cooling Air Flow, m<sup>3</sup>/min (cfm)</b>	13066(370)	17022(482)
<b>Coolant Capacity, l</b>	33.2	

Intake & Exhaust System	1500rpm	1800rpm
<b>Air Flow Combustion at Standby Power, m<sup>3</sup>/min(cfm)</b>	646(18.3)	833.4(23.6)
<b>Heat Rejection Exhaust at Standby Power, KW</b>	231	267
<b>Exhaust Gas Temperature at Standby °C</b>	574	512
<b>Max Allowable Back Pressure in Exhaust Line, Kpa</b>	10.0	10.0
<b>Exhaust Gas Flow at Standby Power, m<sup>3</sup>/min(cfm)</b>	1765.7(50)	2105(59.6)

Accessories	
<b>Oil Drain Pump</b>	<b>Anti-Vibration Pads</b>
<b>Stainless Steel Flexible</b>	<b>Battery Disconnect Switch</b>
<b>Standard Silencer</b>	<b>Fuel Tank Base Frame for 8hrs</b>

Control Panel Readings
<ul style="list-style-type: none"> <li>• AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.</li> <li>• Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load</li> <li>• Oil pressure, water temperature, low oil level, high oil temperature</li> <li>• DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure</li> <li>• Low coolant level - Configurable inputs&amp;outputs</li> <li>• Upgradable for GSM network connection, Signal SMS messages.</li> </ul>

Optional Equipment
<ul style="list-style-type: none"> <li>• <b>Engine</b></li> <li>-Coolant heater</li> <li>-Oversize batteries</li> <li>-Extra fuel pre-filter water separator</li> <li>• <b>Alternator</b></li> <li>-Permanent magnet generator (PMG)</li> <li>-Upgrade to 3 phase sensing AVR</li> <li>-Qadrature droop kit</li> <li>-Anti-condensation heater</li> <li>-Air inlet filters</li> <li>• <b>General</b></li> <li>-Upgrade to modular controller for paralleling</li> <li>-Upgrade to 4 pole circuit breaker</li> <li>-Battery charger</li> <li>-Automatic transfer switch</li> <li>-Fuel level switch High / Low for alarm and control</li> <li>-Fuel transfer pump Automatic / Manual</li> <li>-Residential grade silencer</li> <li>-Weather protective and acoustic enclosure.</li> </ul>

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(1)
Fuel filter	(1)
Fuel pre-filter water separator	(1)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information
<ul style="list-style-type: none"> <li>• <b>Documentation</b></li> <li>Engine instruction book-English</li> <li>Alternator manual- English</li> <li>Wiring diagram</li> </ul>

Warranty
One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.