

GORAN GENERATOR

GGC550 GENSET

Generating Set Powered By



STAMFORD



Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	400KWe / 500KVA	440KWe / 550KVA
1800rpm, 60 Hz / 440V	360KWe / 450KVA	400KWe / 500KVA

Genset Specifications

Engine Make & Model	Cummins QSX15G8
Origin	USA
Alternator Type	Stamford HCI544D
Control Panel	Deap Sea - 7310
Circuit Breaker Type	3 Pole MCCB
Water Cooling System	
Electronic Governor	
Emission Compliant	

Fuel System

	%50	%75	%100
1500rpm, 50 Hz	55	79	105
1800rpm, 60Hz	53.4	77.5	102

*Prime Power (l/hr)

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG32-I, IEC34 CSA C-22.2100, AS 1359, BS 1 6861, B En -6-610002:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. $1 \text{ hp} = 1 \text{ kW} \times 1.36$

Engine Technical Data


No. of Cylinders / Alignment	6/ In Line
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct HPI-TP
Bore, mm	137
Stroke, mm	169
Displacement, l	15
Compression Ratio	17.0:1
Starting	24V Electric
Alternators, Amps	24V/35A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440
Protection	IP23
Temperature Rise, °C	125
Regulation	%1.0±
No. of Phases	3
No. of Poles	4

Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
3.67	1.41	2.0	3750	380



GGC550 GENSET

Generating Set Powered By



STAMFORD

Performances 1500rpm 1800rpm

Alternator Efficiency %94.3 %94.6

Engine Power

Prime Power, KWm(hp) 571(426) 513(383)
Standby Power, KWm(hp) 639(477) 561(419)

Alternator

Prime Power, KWe 440 475

Lubrication System 1500rpm 1800rpm

Oil Consumption (l/hr) 0.03 0.03

Oil Sump Capacity, l 83

Oil System Capacity Include Filters, l 91

Cooling System 1500rpm 1800rpm

Heat Radiation from Engine and Alternator, Power KW 40 36

Heat Rejection to Coolant and Lube Oil at Standby Power, KW 167 130

Radiator Cooling Air Flow, m³/s 11.8 11.8

Coolant Capacity, l 66

Intake & Exhaust System 1500rpm 1800rpm

Air Flow Combustion at Standby Power, m³/min(cfm) 1280(36.3) 1290(36.48)

Heat Rejection Exhaust at Standby Power, KW 390 329

Exhaust Gas Temperature at Standby °C 515 443

Max Allowable Back Pressure in Exhaust Line, Kpa 10 10

Exhaust Gas Flow at Standby Power, m³/min(cfm) 2900(82.2) 3200(90.6)

Accessories

Oil Drain Pump Anti-Vibration Pads

Stainless Steel Flexible Genuine Oil

Oil (VDS40/15 3) Genuine Coolant

Coolant 'Ready Mix' Fuel Tank Base Frame for 8hrs

Standard Silencer

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

• Engine

- Coolant heater
- Oversize batteries
- Extra fuel pre-filter water separator
- Battery Disconnect Switch
- Electrical Governor

• Alternator

- Excitation Boost System (EBS)
- Upgrade to 3 phase sensing AVR
- Qadrature droop kit
- Anti-condensation heater
- Air inlet filters

• General

- Upgrade to modular controller for paralleling
- Upgrade to 4 pole circuit breaker
- Battery charger
- Automatic transfer switch
- Fuel level switch High / Low for alarm and control
- Fuel transfer pump Automatic / Manual
- Residential grade silencer
- Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)

Genuine - Cummins

Oil filter (1)
Fuel filter (1)
Air filter (1)
Fan belt set (1)
Coolant filter (1)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

GORAN

GENERATOR

✉ gorangenerator@gorangroup.com

🏠 Iraq-Erbil-60M str.

☎ 07504483162 - 07704483162

🌐 www.gorangroup.com