

GORAN GENERATOR



GGC900 GENSET

Generating Set Powered By



STAMFORD

Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	648KWe / 810KVA	720KWe / 900KVA
1800rpm, 60 Hz / 440V	727KWe / 909KVA	800KWe / 1000KVA

Genset Specifications

Engine Make & Model	Cummins QSK23G3
Origin	India
Alternator Type	Stamford HCI634G
Control Panel	Deap Sea - 7310
Circuit Breaker Type	3 Pole MCCB
Water Cooling System	
Electronic Governor	
Emission Compliant	

Fuel System

	50%	75%	100%
1500rpm, 50 Hz	85	121	161
1800rpm, 60Hz	97	139	189

*Prime Power (l/hr)

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. $1 \text{ hp} = 1 \text{ kW} \times 1.36$

Engine Technical Data


No. of Cylinders / Alignment	6 In Line
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	170
Stroke, mm	170
Displacement, l	23.1
Compression Ratio	16:1
Starting	24V Electric
Alternators, Amps	24V/35A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX321
Protection	IP23
Temperature Rise, °C	125
Regulation	±0.5%
No. of Phases	3
No. of Poles	4

Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
4.45	1.70	2.15	6350	N/A



GGC900 GENSET

Generating Set Powered By



STAMFORD

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Lubrication System

	1500rpm	1800rpm
Oil Consumption (l/hr)	0.03	0.03

Oil Sump Capacity,l	95
---------------------	----

Oil System Capacity Include Filters,l	103
---------------------------------------	-----

Cooling System

	1500rpm	1800rpm
Heat Radiation from Engine and Alternator, Power KW	71	85

Heat Rejection to Coolant and Lube Oil at Standby Power, KW	222	269
---	-----	-----

Radiator Cooling Air Flow, m ³ /s	13.5	16.6
--	------	------

Coolant Capacity, l	156.5
---------------------	-------

Intake & Exhaust System

	1500rpm	1800rpm
Air Flow Combustion at Standby Power, m ³ /min(cfm)	53.28(1882)	67.92(2398)

Heat Rejection Exhaust at Standby Power, KW	570	656
---	-----	-----

Exhaust Gas Temperature at Standby °C	543	514
---------------------------------------	-----	-----

Max Allowable Back Pressure in Exhaust Line, Kpa	10.2	10.2
--	------	------

Exhaust Gas Flow at Standby Power, m ³ /min(cfm)	147.78(5218)	183.36(6475)
---	--------------	--------------

Accessories

Oil Drain Pump	Anti-Vibration Pads
----------------	---------------------

Stainless Steel Flexible	Genuine Oil
--------------------------	-------------

Oil (VDS3 15/40)	Genuine Coolant
------------------	-----------------

Coolant 'Ready Mix'	Fuel Tank Base Frame for 8hrs
---------------------	-------------------------------

Standard Silencer

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
 - Battery Disconnect Switch
 - Electrical Governor
- **Alternator**
 - Excitation Boost System (EBS)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional) Genuine - Cummins

Oil filter	(2)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Coolant filter	(1)

General Information

Documentation

Engine instruction book-English
 Alternator manual- English
 Wiring diagram

Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

GORAN

GENERATOR

✉ gorangenerator@gorangroup.com 🏠 Iraq-Erbil-60M str.

☎ 07504483162 - 07704483162 🌐 www.gorangroup.com