

Ratings @ 0.8 PF		Prime Rating	Stand-by Rating
Voltage* <sup>1</sup>	Frequency* <sup>2</sup>	KT3.5* <sub>3</sub>	KT3.7S* <sub>4</sub>
230 V	50 Hz	3.5 kVA	3.7 kVA

The above ratings represent the generating set capability guaranteed within ±5% at the reference conditions equivalent to those specified in ISO 3046-part1



## Notes

1. The applicable voltage range is 380V to 415V for 50Hz applications and 380V to 480V for 60Hz applications.

2. This generating set is of switchable speed 1500rpm/1800rpm.

3. KT3.5 is the prime power rating of the generating set, where a variable load and unlimited hours usage are applied on the generating set with load that does not exceed a 70% average of the Prime Power rating during any operating period of 250 hours. The total operating time at 100% Prime Power shall not exceed 500 hours per year. A 10% overload capability is available for a period of 1 hour within a 12-hour period of operation. Total operating time at the 10% overload power shall not exceed 25 hours per year.

4. KT3.7S is a standby power rating of the generating set, where a variable load of maximum of an 80% average load factor and 200 hours of operation per year. This includes less than 25 hours per year at the Standby Power rating. Noting that no overload is permitted.

## Engine Technical Data

Make & Model	KUBOTA Z482		
Cylinders & Arrangement	2; Vertical in-line		
Bore & Stroke (mm)	67 x 68		
Induction system	Naturally aspirated		
Combustion	Indirect injection		
Cycle	4 stroke		
Compression ratio	22:1		
Cooling System	Water cooled		
Displacement	0.479 liters		
Lube oil capacity	2.5 liters Max		
Coolant capacity	2.8 liters		
Standard governor	Electronic		
Engine Speed	1500 rpm		
Fuel Consumption (L/H) @ 100% Load	1.0	@ 50% Load	0.6
Fuel Consumption L/H) @ 75% Load	0.8	@ 25% Load	0.35
Radiator Cooling Air Flow (m <sup>3</sup> /s)	0.35		
Emissions regulations	For non-regulated territories		
Exhaust temperature °C (max)	500		
Max exhaust gas flow (m <sup>3</sup> /min)	1.2		
Max. allowed back pressure (kPa)	7.1		

The above performance data are valid as per the following specs:

- Diesel Fuel is according to BS2869 Class A2 or equivalent.
- Lubricating oil is according to Grade SAE 15W-40 API CI4.
- The coolant should be 50% antifreeze and 50% fresh water.

## Certifications



- The complete Generating Set is type-tested according to ISO 8528-8 Standard.



ISO 17025  
ACCREDITED  
LABORATORY

- The control panel is certified by an ISO 17025 accredited laboratory to have IP55 according to IEC 60355



Quality  
ISO 9001  
SAI GLOBAL

## Dimensions

<b>Length</b>	1200 mm
<b>Width</b>	610 mm
<b>Height</b>	1020 mm
<b>Weight</b>	245 Kg

## Alternator Technical Data

Make & Model	Linz E1X13S A/4		
Frequency / No. of poles	50Hz	Voltage regulation	AVR HVR11
Ingress protection	IP21	Coolant air flow	0.22 m <sup>3</sup> /s
Insulation class	H		
Terminals	2		

## Control Panel Specifications

GMP260MK (DSE6010 MKII) panel is an automatic start generating set panel of microprocessor-based design which is capable of interfacing with electronic engine through the can-bus J1939. It is fully configurable by PC software, yet most settings can be programmed by front fascia buttons. If Mains voltage is to be monitored, DSE6020MKII can be offered.

Circuit Breaker Schneider or ABB, 3 Pole MCB (4 Pole available as Optional)



## Construction

Sheet Fabrication	CNC shearing & bending
Paint type	Heat-treated powder-coated
Paint application	Electrostatic corona spraying
Durability tests	• IMPACT [EN ISO 6272]
	• Salt spray resistance [ASTM B117-73]
Compliance	• Humidity Resistance [ASTM D2247]
	• Panel is compliant with [ISO8528-8]
	• Clearance & Creepage [IEC60355-1]
Degree of protection	• Leakage current & Dielectric strength [IEC60355-1]
	• Protection against electric shock [IEC600 364-4-41]
Wire crimping	Degree of protection IP55
	• Crimping force up to 20KN
	• Accuracy of 0.01mm
Wire coding	• Each crimping is checked by Komax CFA+
	• Wires are coded by wire color and cross-section
	• Wires are coded by printed numbers
	• Wires are coded by printed function of the wire

## Protection (standard)

(OPTIONAL Note <sup>1,3</sup>)

## Control (standard)

(OPTIONAL Note <sup>1</sup>)

## Instrumentation (standard)

(OPTIONAL Note <sup>1,3</sup>)

Over /Under AC voltage	High oil temperature	Remote start input	Battery Charger: 5A, 10A, UL	Gen AC Voltage: 3ph VLL & VLN	Lube oil temperature
Over /Under frequency	High exhaust temperature	Emergency Stop button	Fuel pump control	Gen Frequency: Hz	Exhaust temperature
Delayed Over current	Low fuel pressure	Common Alarm volt-free contact	Extension:	Gen Current: 3 phase A	Engine Inlet air (Boost) pressure
Short-circuit	Low coolant pressure	Event log ( events)	Ethernet –Modbus TCP	Power: KW, KVA, KVAR & PF	Charging ammeter
Over KW	Low fuel level	Weekly Exerciser	RS485- Modbus RTU	Energy: KWhr, KVAhr, KVARhr	Fuel pressure
High Engine Temperature	Low oil level	Audible Alarm	GPS tracker	Lube Oil pressure	Coolant pressure
Low oil pressure	High winding temperature	Standard CANbus J1939	Water in Fuel Detection	Engine coolant temperature	Fuel level
Maintenance Alarm	High bearing temperature	Pre/Post heat control	Webnet Applications	Battery DC Voltage	Lube oil level
High/Low Battery voltage	Low boost pressure	Data Logging	SNMP Gateway	DC Alternator Voltage	Winding temperature 3xRTD
Low coolant level Note 2	Fusible link fire protection	PLC Editor	Inputs: 20 <sup>ma</sup> , 10V	Engine Speed	Bearing temperature RTD
3 ph Mains Sensing (6120)	Low coolant temperature	Oil Level Control	Thermocouples	Operating hours	Tier 4 Support

Note 1: some OPTIONAL features could be standard if CANbus is established within electronic engines.

Note 2: Low coolant level protection is standard feature for Gensets above 200KVA, otherwise it is optional.

Note 3: There is limitation in the number of protections and measurements that can be offered with GMP260MK.

Other types of control Panels & Modules can be offered according to required specifications (DSE 7310/20, 7410/20, 8610, 8810 and Others).

## Genset Standard Features

### Assembly:

Gensets are assembled at Ghaddar Machinery Factory in compliance with ISO 8528-8 standard.

### Fabrication:

- The engine/alternator assembly rests on skid with Anti-vibration mounting pads.
- The skid is made up of durable sheet metals and beams exceeding "Vibration & Torsion" Resistance Norms.
- A skid mounted fuel tank is supplied with fuel gauge, filler cap, fuel inlet and outlet hoses.
- The control panel enclosure is made up of metal sheet .

### Paint:

- The skid and control panel enclosure are painted with heat-treated and power-coated electrostatic corona spraying.
- Paints passed durability tests conforming to international quality standards.
- Impact (EN ISO 6272)
- Salt Spray Resistance (ASTM B117-73)
- Humidity Resistance (ASTM D2247)

### Works-Testing:

- All Gensets are tested prior to dispatch.
- Test is automatically generated and checked according to ISO8528
- Test certificate is issued for each Genset

### Equipment:

- Water cooled Radiator with belt driven blower fan and full guarding
- Electric starter with solenoid Relay
- Battery Charging Alternator
- Energized to run solenoid
- Replaceable fuel, oil and air filters
- Heavy duty leads acid battery with matching capacity (Amps & CCA)
- One loose supplied industrial exhaust silencer – 16 DB noise reduction level.
- Integral Fuel Tank with 67 L capacity.

### Documentation:

- User Manual for Operation, Installation and Maintenance guidance
- Wiring Diagram.
- Test Report
- Maintenance Schedule
- Catalogues for Engine, Alternator & AVR

## Genset Optional Features

- Manual & Automatic Transfer Switches,
- Synchronizing & Totalizing Panels
- Fuel water separator
- Water jacket heater
- Oil heater
- Fuel heater
- Battery heater
- Anti-condensation Heater
- Air Shut-off Valve
- Oil Sampler
- Pre-lube Oil Pump